# Y SERIES DRUM TOPPER



## **Compact and Portable!**

Compact and portable, the DT-Y Drum Topper is designed to fit perfectly on top of a 55-gallon drum. When portability and convenience is of the utmost importance, the Drum Topper has your back. It has the ability to filter oil viscosities up to 600cSt (ISO VG 680) at 100F within ambient temperature ranges of -15F to 150F. All Y2K products are 100% customizable upon request.

# **Typical Applications**

- · Pre-filtering new oil
- Transferring oils
- Topping off reservoirs
- Dispensing new oil





# Y SERIES DRUM TOPPER

Don't see the options you need? Contact Y2K at 1(888) 925-8882 or sales@y2kfluidpower.com

### **Performance:**

For filtering mineral and synthetic based oils (hydraulic oils, gear oils and turbine oils) with a maximum operating viscosity range of ISO VG 690 (3000ssu/648cSt) at 100F within ambient temperature ranges of -15F to 150F

### **Standard Features:**

#### Materials:

- Frame: Heavy duty steel frame
- Paint: Multiple color options available
- Motor: 1/4HP, 115vac, 60Hz
- Filter Heads: Low pressure, aluminum heads
- Pump: Heavy duty, steel gear pump. Available in 1, 2 and 5 GPM
- · Connections: Various quick connect options available
- Hoses: 7ft. Clear PVC, steel reinforced hose or hydraulic hose
- Power Switch: Sealed On/Off Power Switch

#### Filter Indicators:

 Pop up indicator triggers at 25psid when elements need to be changed.

#### Pump Relief:

Opens at 65psi

#### Weight:

Approx. 38lbs (will vary depending on options)

#### Dimensions:

Approx. 20"L x 12"W x 15"H

# **Replacement Elements:**

Part Number	BETA Rating	Desired Cleanliness Level (ISO Code)
P10071	ß3(c)=1000	14/12/9 - 13/11/8
P1007	ß5(c)=1000	15/13/10 - 14/12/9
P1011	ß7(c)=1000	17/15/12 - 15/13/10
P1024	ß12(c)=1000	19/17/14 - 17/15/12
P1010	ß22(c)=1000	21/19/16 - 19/17/14
P1008L	Water Removal	
P1008	Water Removal	

All Y Series elements measure 3" x 8" except the P1008, it measures 3" x 4".

## **Components:**

Item Number	Description	Qty.
1	Frame	1
2	Motor	1
3	Pump	1
4	Filter Head	2
5	Filter Element	2
6	Filter Indicator	2
7	Switch On/Off	1
8	Cord	1



Y2K FLUID POWER

